

印字	型号	厂家	类型	封装	备注
Z	BB145B	Phi	I	SOD 523	Low Voltage Varicap
Z0	SST310	Tem	F	SOT23	J310 n-ch jfet
Z0	PDZ2.4B	Phi	I	SOD323	2.4V 0.4W zener
Z08	SST308	Sil	F	SOT23	J308 n-ch jfet
Z09	SST309	Sil	F	SOT23	J309 n-ch jfet
Z1	BB145B-01	Phi	I	SOD 723	Low Voltage Varicap
Z1	BZX84-C4V7	Phi	C	SOT23	0.3W zener 4.7V
Z1	SSTJ211	Sil	F	SOT23	J211 n-ch jfet
Z1	PDZ2.7B	Phi	I	SOD323	2.7V 0.4W zener
Z1	IMZ1A	Roh	DE		2SC2414 npn,2SA1037AK pnp
Z1	BZV49C4V7	Zet	O	SOT89	1W ±5% zener 4.7V
Z1	BZV49C10	Zet	O	SOT89	1W ±5% zener 10V
Z10	SST310	Sil	F	SOT23	J310 n-ch jfet
Z10	SST310	Sil	F	SOT23	J310 n-ch jfet
Z11	BZX84-C2V4	Phi	C	SOT23	0.3W zener 2.4V ±5%
Z12	BZX84-C2V7	Phi	C	SOT23	0.3W zener 2.7V ±5%
Z13	BZX84-C3V0	Phi	C	SOT23	0.3W zener 3.0V ±5%
Z14	BZX84-C3V3	Phi	C	SOT23	0.3W zener 3.3V ±5%
Z15	BZX84-C3V6	Phi	C	SOT23	0.3W zener 3.6V ±5%
Z16	BZX84-C3V9	Phi	C	SOT23	0.3W zener 3.9V ±5%
Z17	BZX84-C4V3	Phi	C	SOT23	0.3W zener 4.3V ±5%
Z2	BZX84-C5V1	Phi	C	SOT23	0.3W zener 4.7V
Z2	SSTJ212	Sil	F	SOT23	J212 n-ch jfet
Z2	IMZ2A	Roh	DF		2SC2414 npn,2SA1037AK pnp
Z2	PDZ3.0B	Phi	I	SOD323	3.0V 0.4W zener
Z2	BZV49C5V1	Zet	O	SOT89	1W ±5% zener 5.1V
Z21	DTC113ZE	Rho	N	EMT3	npn dtr 1k0 + 10k 50V 100mA
Z21	DTC113ZUA	Rho	N	SC70	npn dtr 1k0 + 10k 50V 100mA
Z21	DTC113ZKA	Rho	N	SC59	npn dtr 1k0 + 10k 50V 100mA
Z2U	FMMTA63	Zet	N	SOT23	MPSA63
Z2V	FMMTA64	Zet	N	SOT23	MPSA64
Z3	BZX84-C5V6	Phi	C	SOT23	0.3W zener 5.6V
Z3	PDZ3.3B	Phi	I	SOD323	3.3V 0.4W zener
Z3	2SK1078	Tos	T	SOT89	n-ch mosfet 60V 0.8A
Z3	BZV49C5V6	Zet	O	SOT89	1W ±5% zener 5.6V
Z4	BZX84-C6V2	Phi	C	SOT23	0.3W zener 6.2V
Z4	PDZ3.6B	Phi	I	SOD323	3.6V 0.4W zener
Z4	2SK1079	Tos	T	SOT89	n-ch mosfet 100V 0.6A
Z4	BZV49C6V2	Zet	O	SOT89	1W ±5% zener 6.2V
Z5	BZX84-C6V8	Phi	C	SOT23	0.3W zener 6.8V
Z5	PDZ3.9B	Phi	I	SOD323	3.9V 0.4W zener
Z5	2SK1717	Tos	T	SOT89	n-ch mosfet 60V 2A
Z5	BZV49C6V8	Zet	O	SOT89	1W ±5% zener 6.8V
Z50	BZX84-B2V4	Phi	C	SOT23	0.3W zener 2.4V ±2%

Z51	BZX84-B2V7	Phi	C	SOT23	0.3W zener 2.7V \pm 2%
Z52	BZX84-B3V0	Phi	C	SOT23	0.3W zener 3.0V \pm 2%
Z53	BZX84-B3V3	Phi	C	SOT23	0.3W zener 3.3V \pm 2%
Z54	BZX84-B3V6	Phi	C	SOT23	0.3W zener 3.6V \pm 2%
Z55	BZX84-B3V9	Phi	C	SOT23	0.3W zener 3.9V \pm 2%
Z56	BZX84-B4V3	Phi	C	SOT23	0.3W zener 4.3V \pm 2%
Z57	BZX84-B4V7	Phi	C	SOT23	0.3W zener 4.7V \pm 2%
Z58	BZX84-B5V1	Phi	C	SOT23	0.3W zener 5.1V \pm 2%
Z59	BZX84-B5V6	Phi	C	SOT23	0.3W zener 5.6V \pm 2%
Z6	BZX84-C7V5	Phi	C	SOT23	0.3W zener 7.5V
Z6	PDZ4.3B	Phi	I	SOD323	4.3V 0.4W zener
Z6	2SJ238	Tos	T	SOT89	p-ch mosfet 60V 1A
Z6	BZV49C7V5	Zet	O	SOT89	1W \pm 5% zener 7.5V
Z60	BZX84-B6V2	Phi	C	SOT23	0.3W zener 6.2V \pm 2%
Z61	BZX84-B6V8	Phi	C	SOT23	0.3W zener 6.8V \pm 2%
Z62	BZX84-B7V5	Phi	C	SOT23	0.3W zener 7.5V \pm 2%
Z63	BZX84-B8V2	Phi	C	SOT23	0.3W zener 8.2V \pm 2%
Z64	BZX84-B9V1	Phi	C	SOT23	0.3W zener 9.1V \pm 2%
Z65	BZX84-B10	Phi	C	SOT23	0.3W zener 10V \pm 2%
Z66	BZX84-B11	Phi	C	SOT23	0.3W zener 11V \pm 2%
Z67	BZX84-B12	Phi	C	SOT23	0.3W zener 12V \pm 2%
Z68	BZX84-B13	Phi	C	SOT23	0.3W zener 13V \pm 2%
Z69	BZX84-B15	Phi	C	SOT23	0.3W zener 15V \pm 2%
Z7	BZX84-C8V2	Phi	C	SOT23	0.3W zener 8.2V
Z7	PDZ4.7B	Phi	I	SOD323	4.7V 0.4W zener
Z7	BZV49C8V2	Zet	O	SOT89	1W \pm 5% zener 8.2V
Z70	BZX84-B16	Phi	C	SOT23	0.3W zener 16V \pm 2%
Z71	BZX84-B18	Phi	C	SOT23	0.3W zener 18V \pm 2%
Z72	BZX84-B20	Phi	C	SOT23	0.3W zener 20V \pm 2%
Z73	BZX84-B22	Phi	C	SOT23	0.3W zener 22V \pm 2%
Z74	BZX84-B24	Phi	C	SOT23	0.3W zener 24V \pm 2%
Z75	BZX84-B27	Phi	C	SOT23	0.3W zener 27V \pm 2%
Z76	BZX84-B30	Phi	C	SOT23	0.3W zener 30V \pm 2%
Z77	BZX84-B33	Phi	C	SOT23	0.3W zener 33V \pm 2%
Z78	BZX84-B36	Phi	C	SOT23	0.3W zener 36V \pm 2%
Z79	BZX84-B39	Phi	C	SOT23	0.3W zener 39V \pm 2%
Z8	BZX84-C9V1	Phi	C	SOT23	0.3W zener 9.1V
Z8	PDZ5.1B	Phi	I	SOD323	5.1V 0.4W zener
Z8	BZV49C9V1	Zet	O	SOT89	1W \pm 5% zener 9.1V
Z80	BZX84-B43	Phi	C	SOT23	0.3W zener 43V \pm 2%
Z81	BZX84-B47	Phi	C	SOT23	0.3W zener 47V \pm 2%
Z82	BZX84-B51	Phi	C	SOT23	0.3W zener 51V \pm 2%
Z83	BZX84-B56	Phi	C	SOT23	0.3W zener 56V \pm 2%
Z84	BZX84-B62	Phi	C	SOT23	0.3W zener 62V \pm 2%
Z85	BZX84-B68	Phi	C	SOT23	0.3W zener 68V \pm 2%

Z86	BZX84-B75	Phi	C	SOT23	0.3W zener 75V \pm 2%
Z9	BZX84-C10	Phi	C	SOT23	0.3W zener 10V
Z9	PDZ5.6B	Phi	I	SOD323	5.6V 0.4W zener
ZA	BZX284-C7V5	Phi	I	SOD110	0.4W zener 7.5V \pm 5%
ZA	PDZ6.2B	Phi	I	SOD323	6.2V 0.4W zener
ZB	FMMT4123	Zet	N	SOT23	2N4123
ZB	PDZ6.8B	Phi	I	SOD323	6.8V 0.4W zener
ZB	BZX284-C8V2	Phi	I	SOD110	0.4W zener 8.2V \pm 5%
ZC	FMMT4124	Zet	N	SOT23	2N4124
ZC	BZX284-C9V1	Phi	I	SOD110	0.4W zener 9.1V \pm 5%
ZC	PDZ7.5B	Phi	I	SOD323	7.5V 0.4W zener
ZD	FMMT4125	Zet	N	SOT23	2N4125
ZD	MMBT4125	Mot	N	SOT23	2N4125
ZD	BZX284-C10	Phi	I	SOD110	0.4W zener 10V \pm 5%
ZD	PDZ8.2B	Phi	I	SOD323	8.2V 0.4W zener
ZE	FMMT4126	Zet	N	SOT23	2N4126
ZE	MMBT4123	Nat	N	SOT23	2N4123
ZE	BZX284-C11	Phi	I	SOD110	0.4W zener 11V \pm 5%
ZE	PDZ9.1B	Phi	I	SOD323	9.1V 0.4W zener
ZF	BZX284-C12	Phi	I	SOD110	0.4W zener 12V \pm 5%
ZF	PDZ10B	Phi	I	SOD323	10V 0.4W zener
ZG	BZX284-C13	Phi	I	SOD110	0.4W zener 13V \pm 5%
ZG	PDZ11B	Phi	I	SOD323	11V 0.4W zener
ZH	BZX284-C15	Phi	I	SOD110	0.4W zener 15V \pm 5%
ZH	PDZ12B	Phi	I	SOD323	12V 0.4W zener
ZHK	SM2Z5V1	STM	I	2W SMD	5.1V 2W zener
ZHL	SM2Z5V6	STM	I	2W SMD	5.6V 2W zener
ZHW	SM2Z12	STM	I	2W SMD	12V 2W zener
ZI	BZX284-C16	Phi	I	SOD110	0.4W zener 16V \pm 5%
ZJ	BZX284-C18	Phi	I	SOD110	0.4W zener 18V \pm 5%
ZJ	PDZ13B	Phi	I	SOD323	13V 0.4W zener
ZJF	SM2Z18	STM	I	2W SMD	18V 2W zener
ZJQ	SM2Z30	STM	I	2W SMD	30V 2W zener
ZK	BZX284-C20	Phi	I	SOD110	0.4W zener 20V \pm 5%
ZK	PDZ15B	Phi	I	SOD323	15V 0.4W zener
ZKR	SM2Z150	STM	I	2W SMD	150V 2W zener
ZL	BZX284-C22	Phi	I	SOD110	0.4W zener 22V \pm 5%
ZL	PDZ16B	Phi	I	SOD323	16V 0.4W zener
ZM	BZX284-C24	Phi	I	SOD110	0.4W zener 24V \pm 5%
ZM	PDZ18B	Phi	I	SOD323	18V 0.4W zener
ZN	BZX284-C27	Phi	I	SOD110	0.4W zener 27V \pm 5%
ZN	PDZ20B	Phi	I	SOD323	20V 0.4W zener
ZO	BZX284-C30	Phi	I	SOD110	0.4W zener 30V \pm 5%
ZP	BZX284-C33	Phi	I	SOD100	0.4W zener 33V \pm 5%
ZP	PDZ22B	Phi	I	SOD323	22V 0.4W zener

ZQ	BZX284-C36	Phi	I	SOD110	0.4W zener 36V \pm 5%
ZQ	PDZ24B	Phi	I	SOD323	24V 0.4W zener
Z-Q	2PC4081Q	Phi	N	SOT323	gp npn hfe 120-270
ZR	MSD1819A	Mot	N	SOT323	npn gp 50V
ZR	BZX284-C39	Phi	I	SOD110	0.4W zener 39V \pm 5%
ZR	PDZ27B	Phi	I	SOD323	27V 0.4W zener
Z-R	2PC4081R	Phi	N	SOT323	gp npn hfe 180-390
ZS	BZX284-C43	Phi	I	SOD110	0.4W zener 43V \pm 5%
ZS	PDZ30B	Phi	I	SOD323	30V 0.4W zener
Z-S	2PC4081S	Phi	N	SOT323	gp npn hfe 270-560
ZS1	ZHCS1000	Zet	E	SOT23	30V 1A schottky diode
ZS1	ZHCS1000	Zet	C	SOT23	schottky 1A 30V
ZS5	ZHCS500	Zet	E	SOT23	40V 0.5A schottky diode
ZS7	ZHCS750	Zet	E	SOT23	30V 0.75A schottky diode
ZS7	ZHCS750	Zet	C	SOT23	schottky 0.75A 30V
ZT	BZX284-C47	Phi	I	SOD110	0.4W zener 47V \pm 5%
ZT	PDZ33B	Phi	I	SOD323	33V 0.4W zener
ZtQ	2PC4081Q	Phi	N	SOT323	gp npn hfe 120-270
ZtR	2PC4081R	Phi	N	SOT323	gp npn hfe 180-390
ZtS	2PC4081S	Phi	N	SOT323	gp npn hfe 270-560
ZU	BZX284-C51	Phi	I	SOD110	0.4W zener 51V \pm 5%
ZU	PDZ36B	Phi	I	SOD323	36V 0.4W zener
ZV	BZX284-C56	Phi	I	SOD110	0.4W zener 56V \pm 5%
ZW	BZX284-C62	Phi	I	SOD110	0.4W zener 62V \pm 5%
ZX	BZX284-C68	Phi	I	SOD110	0.4W zener 68V \pm 5%
ZY	BZX284-C75	Phi	I	SOD110	0.4W zener 75V \pm 5%